





## **Specifications**

WAN Interface	2x 10/100/1000M Ethernet <sup>2</sup> 4x Embedded Cellular Modems with Redundant SIM Slots 1x USB 2.0 Interface <sup>3</sup>	Antennas	8x Internal Cellular Antennas 4x Internal Wi-Fi Antennas 1x Internal GPS Antenna
LAN Interface	2x External 10/100/1000M Ethernet 5x 10/100/1000M Ethernet <sup>2</sup>	Power Input	DC : 12V - 56V AC : 100V - 240V
		Power Output	Up to 7x 802.3at PoE, 4x USB Power Outputs
Wi-Fi Interface	802.11ac/a/b/g/n, 1166 Mbps 2x2 MIMO Wi-Fi WAN and/or AP Simultaneous Dual-Band	Power Consumption	38W (max.)
		Dimension	19.8 x 15.8 x 7.4 inches / 502 x 401 x 188mm
PDX Throughput	2.5 Gbps	Weight	35.0 pounds / 15.9 kg
PepVPN Throughput	500.44		400 4400 450
- No Encryption - 256-bit AES	600 Mbps 500 Mbps	Operating Temperature	-40° – 113°F / -40° – 45°C
- 250-bit ALS	300 Mbp3	Humidity	15% – 95% (non-condensing)
Recommended Users	50-500	•	, <i>3,</i>
		Certifications	RoHS
Cellular Data Rate (Downlink/Uplink)	CAT-12: 600 Mbps / 150 Mbps CAT-20: 2 Gbps / 211 Mbps		MIL-STD-810H IP55/65
(Downlink/Opink)	CA1-20. 2 dbps / 211 Mbps		1233/03
Recommended Users	50-500	Package Content	1x PDX
			1x Special Power Cord for PDX (ACW-645)
Storage encryption	LUKS		1x Special Car Plug for PDX (ACW-646)
SSD storage	512GB SSD Internal storage		(Batteries not included)
	- · · · · · · · · · · ·	SIM Options	Mini-SIM (2FF)
CPU	E3950	-	Peplink eSIM

Warranty

Specifications are subject to change without notice.

BYO eSIM (2 profiles per modem) RemoteSIM from SIM Injector

1-Year Limited Warranty

FusionSIM

<sup>&</sup>lt;sup>1</sup>The external ports are configured as a LAN port by default, configuration is changeable on the Web Admin. <sup>2</sup> These Ethernet ports can be used with the two WAN/LAN external port. <sup>3</sup> Any one out of the four available ports can serve as a single USB WAN port.





## **Ordering Information**

Product Code	Regions^	LTE Bands	3G Bands
PDX-EC-LTEA-R-T Embedded Modem(s): 4x LTE-A (CAT-12)	North America*  *US Carrier Certifications: AT&T, Verizon, FirstNet, US Cellular	B1, B2, B3, B4, B5, B7, B8, B9, B12, B13, B14, B18, B19, B20, B26, B29, B30, B32, B41, B42, B43, B46, B48, B66	B1, B2, B4, B5, B6, B8, B9, B19
PDX-EC-LTEA-K-T Embedded Modem(s): 4x LTE-A (CAT-12)	EMEA, APAC	B1, B2, B3, B4, B5, B7, B8, B9, B12, B13, B18, B19, B20, B26, B28, B29, B30, B32, B41, B42, B43, B46, B48, B66	B1, B2, B4, B5, B6, B8, B9, B19
PDX-EC-GLTE-S-T Embedded Modem(s): 4x LTE-A (CAT-20)	Global	B1, B2, B3, B4, B5, B7, B8, B12, B13, B14, B17, B18, B19, B20, B25, B26, B28, B29, B30, B32, B34, B38, B39, B40, B41, B42, B46, B48, B66, B71	B1, B2, B4, B5, B6, B8, B9, B19

 $<sup>^{\</sup>wedge}$  Regions are for reference only. For specific location compatibility, please refer to the bands.

## Featured Add-on

Product Code	Description
SVL-499	EssentialCare (1-Year) for PDX
SVL-554	EssentialCare (2-Year) for PDX
ECP-PDX-1Y	EssentialCare+ (1-Year) for PDX
ECP-PDX-2Y	EssentialCare+ (2-Year) for PDX
ECP-PDX-4Y	EssentialCare+ (4-Year) for PDX
PDX-BAT-KIT	PDX Battery Kit, 1x Metal Clamp, 1x Power Cable, 2x M3 Scr, 98Wh, 14.4V